


A. Hotel lock model no. A8-E-A-MF



1)Technical Parameters:

Model No.	A8-E-A-MF			
Lock type	UL certificated Hotel Lock			
Material	SUS304 stainless steel			
Reader area material	ABS			
Lock open solution	RFID card, Mechanical key			
Card type	S50 card, 13.56MHz			
International Standard	ISO14443-A			
Encrypting Elements	48 bits card special logic key encrypting and system data DES			
	encrypting 32 bits card special logic key encrypting and			
	system data DES encrypting			
Working Consumption	≤200mA , working≤0.2 seconds			
Static consumption	≤25u A			
Working Temperature	-20℃~55℃			
Battery unlocking lift	≥20,000 times			
Reliability	≥200,000 times			
Mechanical life	≥200,000 times			
Powered by	4 pieces AA Alkaline battery (6V)			
Low voltage alarm	4.8V(6V power supply)			
Cylinder	Hidden cylinder, mechanical override			
Mortise	ANSI mortise, five latch, deadbolt function			
Mortise size	ANSI: 257.3x28.6x106.1mm			
Panel size				
Package	Each set in one white box, 6 sets per carton			
Carton size	L410 x W340 x H500mm			
Color	Silver			


Add.: #20 Shuitian Rd, Tongle Community, Longgang Town, Shenzhen City, China

www.locstarsmart.com www. locstar.com Sales: I o c s t a r H/P:+86-18988789425



2)Panel size illustration (mm):

3)ANSI Mortise (door thickness≥40MM), five latch, deadbolt.



4) Packaging includes:



Front handle, sensor cover, cylinder cover

Add.: #20 Shuitian Rd, Tongle Community, Longgang Town, Shenzhen City, China




Back handle, deadbolt panel ANSI mortise PCBA box with battery case Accessories for installation Cylinder 2pcs metal key Strike plate Strike box

D. RFID Hotel Door Lock System:

Add.: #20 Shuitian Rd, Tongle Community, Longgang Town, Shenzhen City, China





Hotel Door Locking System includes:			
1. Hotel Lock (Qty = guest room)	to be installed on the door, powered		
1. Hotel Lock (Qty – guest room)	by 4pcs AA batteries		
2. Encoder	to issue all kinds of cards		
3. Energy saving switch (optional, Qty=guest room)	to insert the RF card to get power.		
4. RF cards (S50 card, 13.56MHz)	to set as functions cards and to open		
4. KF Calus (350 Calu, 13.50MHz)	the door		
5. Data collection (optional)	to get the unlocking door record		
6. Software	To set up / manage the guest rooms		

Working Principle:

Add.: #20 Shuitian Rd, Tongle Community, Longgang Town, Shenzhen City, China

www.locstarsmart.com Sales: I o c s t a r H/P:+86-18988789425 www. locstar.com




- 1. The instruction is issued from software through encoder to the RF cards.
- 2. Use the contactless RF card to communicate with the lock.

Operation steps:

- Step 1: Install the hotel door lock software to the computer
- Step 2: Set up the hotel rooms as the hotels requirement. (see below)
- Step 3: Issue the function cards (Authorization card, clock card, room setting card), authorize the lock through the authorization card, then set the time on the lock and room no. one by one.
- Step 4: Issue any card you need to control the lock. (see below the cards function)

Hotel Door Lock Software: manage each hotel room and cards



Cards function:

No.	Card type	Function
1	Authorization card	are basic setting cards ,all new locks after installation on door
2	Clock card	must be set by this three cards first.
3	Room setting card	
4	Lock out card	To close the unused rooms

Add.: #20 Shuitian Rd, Tongle Community, Longgang Town, Shenzhen City, China


www.locstarsmart.com Sales: I o c s t a r H/P:+86-18988789425

	1	inon Ecociai roomiciogy con, Etai			
5	Terminate card	To terminate the function of guest card			
6	check-out card	To terminate the function of guest room card when guest would			
		like to check out ahead of schedule.			
7	Passage card	To set the lock in the long unlocking state.			
8	Alarm card	To set alarm function, when the lock in the condition of false			
		locking and uncompleted locking			
9	No disturbing card	To set no disturbing function in the condition of deadbolt			
10	Master card	Can open all the doors in one hotel ,don't limited on deadbolt and			
		time. Usually, the general manager hold this card.			
11	Emergency card	open the door in the emergency condition and keep lock on the			
		long-unlocking state. Usually, the manager hold this card			
12	Building card	Can open all the doors in a certain building ,limited on deadbolt			
		and time. Usually, the manager hold this card.			
13	Floor card	Can open all the doors in a certain floor ,limited on deadbolt and			
		time. Usually ,the foremen hold this cards			
14	House-keeping card	can open all the doors in a certain clean -rooms. Usually, the			
		clean staff hold this card			
15	Guest room card	open the certain guest room. guest hold this card.			

*MF Hotel Lock System With Elevator Control, Door Access Control:

The hotel lock system work with elevator control, door access control as a complete access control system for hotel or similar project, high security.

Add.: #20 Shuitian Rd, Tongle Community, Longgang Town, Shenzhen City, China



Elevator Co	ontrol System					
1	LS-DT503/513	card reader	PNAME Page and and	The elevator controller system is made of the four items, Supporting MF card .The model DT503 is used for building, and the model DT513 is used for floor. 1, need confirm you need building control, or just for floor control. 2, the quotaiton is based on floors below 16, if the building more than 16floors, each 8 flloors price will be 100usd higher.	\$556.00	
2	LS-DTK01	elevator controller	IIII			
3	LS-DC242A	24V power supply				

Add.: #20 Shuitian Rd, Tongle Community, Longgang Town, Shenzhen City, China



				,	is.	
Access Con	trol System				90	
1	LS-MJ501	Access card reader		This is a standard set of access controller system, which is made of the five items, power supply special for single access, magnetic locks, electric plug lock, Outside button, door clip. 2. supporting MF card access controller. 3. Choose the door clip and locks according to demand, as the color part mark.	\$65.00	Door access system connection diagram
2	LS- WDA802	power supply special for single access(5A)12V	S rates		\$22.00	
3	LS-EF01	Outside button			\$3.00	
4	LS-FJ01	Double open mini door clip			\$6.00	
5	LS-FJ02	U shape door clip			\$11.00	
6	LS-DS280	Magnetic locks for single door, 280KG			\$41.00	
7	LS-DS280D	Magnetic locks for double door, 280KG			\$82.00	
8	LS-DS100S	Electric plug lock			\$25.00	
9	LS-DS500U	Electric plug lock special for frameless the glass door			\$35.00	

Add.: #20 Shuitian Rd, Tongle Community, Longgang Town, Shenzhen City, China

www.locstarsmart.com www. locstar.com Sales: locstar H/P:+86-18988789425